

M.2 MOSAIC GNSS RECEIVER CARD




ALL-IN-VIEW GNSS Satellite tracking: multi-constellation, multi-frequency for fast convergence time

M.2 Key E form factor for the use in industrial PCs and development boards (e.g. Nvidia Jetson)

Advanced Septentrio technology inside: AIM+, LOCK+, APME+, IONO+



High rate RTK solution output



Accurate position and attitude



Small form factor



Breakthrough price



Easy System Integration

PERFORMANCE

Accurate RTK Positioning¹ (1 σ):

Horizontal accuracy: 0.006 m + 1 ppm
Vertical accuracy: 0.010 m + 1 ppm

Accurate Attitude^{1,2} (1 σ):

Antenna separation	Heading	Pitch/Roll
1 m	0.15°	0.25°
5 m	0.03°	0.05°

Velocity Accuracy: 0.03 m/s RMS

Maximum update rate:

Measurements only:	100 Hz
Standalone, SBAS, DGPS + attitude ² :	50 Hz
RTK + attitude ² :	20 Hz
Latency:	< 10ms

¹ Depends on Environment and used GNSS-Antenna

² Only available with MOSAIC-H

Physical and Environmental

Package: Standardized M.2 Key E

Antenna connector type:	MMCX socket
Antenna pre-amplification range:	15-50 dB
Antenna bias voltage:	3.0-5.5 V
	Build-in current limit (150 mA)

Input voltage:	3.3 VDC +/-5%
Power consumption:	0.6 W typ., 1.1 W max
Environmental Operating temp.:	-40 to 85° C
Storage temp.:	-55 to 85° C
Humidity:	5% 95% (non-condensing)
Vibration:	MIL-STD-810G
Certification:	RoHS, WEEE

GNSS FEATURES

GNSS Constellations:

Galileo, GPS, Glonass,
Beidou, SBAS (Egnos, WAAS, GAGAN)

GNSS Const. concurrent:

All

GNSS-Bands³:

GPS: L1C/A, L1C, L1PY, L2C, L2P, L5
GLO: L1CA, L2CA, L2P, L3
GAL: E1, E5a, E5b, E5 AltBoc, E6
BDS: B1I, B1C, B2a, B2I, B3
QZSS: L1C/A, L1C, L2C, L5, L6

³With MOSAIC-X5 Chip

Protocols

Septentrio Binary Format (SBF)
NMEA 0183, v2.3, v3.03, V4.0
RINEX v2.x, v3.x
RTCM v2.x, v3.x (MSM included)
CMR v2.0 (out/in), CMR+ (input only)

M.2 to USB-C Adapter

- M.2 key E to USB Type C adapter
- Flat bottom side for easy mounting on different surfaces
- Dimension: 66 x 22.5 x 7 mm
- Compatible with all standard M.2 key E card sizes
- Screw mount for 42 mm card length. Additional mounting point for 30 mm cards
- USB Type C connector for communication via USB 2.0 and power supply

Pin header for additional signals:

Pin	Signal name
1	SDIO wake (output, 1.8 V level)
2	UART_TXD (input, 1.8 V level)
3	GLOBAL_RESET/SDIO_RESET (input, 1.8 V signaling, weak pull-up)
4	UART_RXD (output, 1.8 V signaling)
5	+3.3 V power output
6	TP_TO_MOD/UART_RTS (input, 1.8 V signaling)
7	+5.0 V power output
8	TP_FROM_MOD/UART_CTS (output, 3.3 V signaling)
9	Ground
10	PM_WAKEUP_N/UART_WAKE_N (output, 3.3 V signaling)

